

E-806 CMOS Indoor Dome Camera



Installation Manual

Budget Style CMOS Indoor Dome Camera
w/3 LUX Color Image Sensor

Camera Installation

1. Camera Mounting:

Items Needed:

Screwdriver, Drill, Mounting Hardware (not included), Glove or Cloth for moving Dome, Pencil

a. Remove Dome



b. Mark wall through Mounting Holes



c. Drill Holes for mounting

d. Drill Hole for Cables

Camera Installation

- e. Connect Cables



Red = Power Connection

White = Audio

Yellow = Video

- f. Insert Drywall Anchors (Drywall Mounting Only *Not Included)
- g. Insert Screws
- h. Adjust camera angle to suit needs
- i. Reinstall Dome



Platinum CCTV Surveillance Solutions

E-806 CMOS Color Dome Camera	
Image Sensor	CMOS 1/3" Color
Number of Pixels	NTSC: 510 (H) x 492 (V)
Scanning System	NTSC: 525 Lines, 60Hz
Sync System	Internal Synchronization
Resolution	380 TVL
Gamma Correction	0.45
Video Output	1.0Vp-p75Ω
S/N Ratio	>45/dB (AGC off)
Shutter Time	1/60-1/100000 Sec.
Operation Temp.	-10°C ~ +50°C
Storage Temp.	-20°C ~ +60°C
Useable Illumination	3 Lux (F:2.0)
Power Source	DC 9V ± 10%

Installation Notes
<ul style="list-style-type: none">• For Indoor Use Only• Disassembly of camera is not recommended• Handle lens carefully with gloves to prevent damage from oil on your hands• Handle with care• To prevent shock, do not plug in camera with dome removed• Never touch lens directly• Clean the dome occasionally with a dry micro-fiber cloth, or plastic cleaner only – Do not use abrasive-type cleaners as they will scratch dome